

Single Channel Modulator, 3 Channel Modulator

CAT NO. **HNMD01, HNMD03**



HNMD01



HNMD03

These modulators allow conversion and distribution of high quality audio and video signals around the home on a wide choice of channels on the UHF Band.

Composite AV signals are accepted through RCA jacks as input and output is modulated signal on user selected RF frequency through a F connector.

Single Channel Modulator

- 1 x composite input
- 1 x F type UHF output
- User frequency select via Dip switch
- Built-in combiner (e.g. TV antenna)
- Gain adjustment
- Power plug and lead

3 Channel Modulator

- 3 x composite inputs
- 1 x F type UHF output
- LED channel display
- Power and MODE SELECT LED indicators
- Easy set-up with MODE SELECT and up/down push buttons
- Gain adjustment
- Power adaptor included
- Comes with 3 sets of audio and video cables

Product specifications	
CAT	HNMD01
Description	Single channel modulator
Voltage	240V a.c. 50Hz
System	PAL-B
No. of composite input	1, RCA jack
No. of RF input	1, F connector
Output	UHF

Product specifications	
CAT	HNMD03
Description	3 channel modulator
Voltage (power adaptor)	240V a.c. 50Hz
Input voltage	9V d.c. (Power adaptor included)
No. of composite input	3, RCA jacks
Output	UHF
Operating temperature	-10°C to +60°C

Packaging specifications		
CAT	HNMD01	HNMD03
Single box quantity	1	1
Single box dimensions	155W x 95H x 235Dmm	240W x 60H x 160Dmm
Single box weight	500g	860g
Single box barcode	9321001391036	9321001391043

HPM Legrand - AUS
1300 369 777
www.hpm.com.au

ABN 31 000 102 661

HPM Legrand - NZ
0800 476 009
www.hpm.co.nz

Single Channel Modulator, 3 Channel Modulator

CAT NO. **HNMD01, HNMD03**

Refer to your group buying office, HPM Legrand Sales Representative or
HPM Legrand Sales Office for pricing.